





Frequency Response



Polar Pattern M

Polar Pattern S



MKH 418S Shotgun Microphone

The MKH 418S is a compact MS stereo shotgun microphone utilizing Sennheiser's exclusive RF condenser microphone technology. The MKH418S incorporates a mid capsule based on that of the legendary MKH416 which is combined with a newly designed figure-of-eight side capsule. Its high constant articulation, excellent feedback rejection and functional versatility make the MKH418S a superb all-round cost-effective choice for film, television, and multi-media applications.

Features and Benefits

- Matt black finished brass body is rugged and weather resistant
- · Low inherent self noise insures an optimal signal to noise ratio
- Rugged MKH capsules are impervious to extreme climate conditions
- Independant capsule outputs allow variable matrixing capabilities and multi-functional use.

Technical Data

Acoustic operating principle

M:pressure gradient/interference tube
S: pressure gradient

M: pressure gradient

Pick-up pattern M: super cardioid/lobar S: figure-of-eight

Sensitivity at 1K Hz M: 25 mV/Pa (-32 dBV) S: 10 mV/Pa (-40 dBV)

Frequency response 40 - 20,000 Hz Max. SPL 130 dB SPL (63 Pa)

Max. output voltage 1.5 V

Equivalent noise level M: 14 dB-A / 26 dB-CCIR S: 22 dB-A / 34 dB-CCIR

Output impedance at 1 kHz < 25 ohms

Min. load impedance 1 kohms

Power supply P48: $48 \pm 4 \text{ V} / 2 \text{ x } 2.3 \text{ mA}$ Connector 5-pin XLR, male Dimensions Ø 19 mm x 280 mm

Weight 220 g

Operating temperature range -20 to +60 °C


Humidity range < 95 % relative humidity

Delivery includes

Case

User manual





Recommended Accessories

MZW415 windscreen AC418 cable, 1m. ACS5 Y cable adapter MZQ 100 mic stand clip MZS20-1 shockmount MZW60-1 basket windshield MZH60-1 hairy cover True Systems P2A mic preamp True Systems Precision 8 Mic Preamp